xcite LED Lighting
Data Sheet

Order Code: XCHBAMS




Features


- **Remote Sensor Programming [XCHBAREM sold separately]**
  Quick configuration of X1 High Bay sensor settings from floor level, with an operating range of up to 15m
- **Simple, Plug & Play Installation**
  Zhaga base connection
- **Scene Setting**
  Detection area, hold time, standby dim level, standby period
- **Detection Area**
  8m radius, 15m maximum installation height, detection angle of 30° to 150°
- **Detection Sensitivity**
  Adjusts the detection sensitivity according to the installation height, or by the selectable values 25%,50%,75% or 100%
- **Corridor Function**
  After the hold time expires, the sensor dims the brightness to the standby level and time required
- **Brightness Adjustable**
  From 10% up to 100%, in 5% increments

Dimensions

C (mm)	31
Dia. (mm)	48

Line Drawing





Technical
Stafford Park 12
Telford, Shropshire,
TF3 3BJ

T: +44 (0)1952 292441
E: sales@xciteledlighting.co.uk
W: www.xciteledlighting.co.uk