

**Order Code: XCBHCBOX1M3MS**

X1 Bulkhead WP - Circular - Opal diffuser - CCT [3000K/4000K/6000K]+ Wattage Selectable - Black - Emergency - Microwave sensor



**Features**

- Suitable for exterior commercial and industrial applications
- Wattage selectable via selector switch [8W/12W/16W]
- CCT selectable via selector switch [3000K/4000K/6000K]

**Construction**

- Modular [emergency](#) and [microwave sensor](#)'s available for quick and easy conversion of a standard fitting
- For additional control, please use [X1 Bulkhead Remote](#) [Sold Separately]

**Installation Notes**

3-point screw fixing  
Conduit side entry points for surface mount cable entry  
Loop-in, loop-out push-fit terminal block for quick tool-free instalation



**Technical Data**

**General**

Luminaire Wattage (W)	8W/12W/16W
Weight (kg)	0.82
Operating Temperature (ta °C)	5° to 25°

**Light Output**

Lumens (lm)	1070 to 1930
Efficacy (lm/W)	128

**LED**

CCT (K)	3000K/4000K/6000K
CRI	80
Macadam Ellipses	1 to 1.5

**Driver**

Driver Current (mA)	140/215/280
Forward Voltage (V)	48.5 to 52.5

**Emergency**

Emergency Lumen Operating	146
Emergency Wattage (W)	2

**Electrical**

Rated Input Current (A)	0.04 to 0.08
Power Factor (pf)	0.83 to 0.92
Input Voltage Range (VAC)	198 to 264
Inrush Current Peak (A)	19.1
Surge Protection (kV)	1
Conductor Size (mm)	0.5 to 2.5
Terminal Type	4 pole piano key

**Order Code: XCBHCBOX1M3MS**

X1 Bulkhead WP - Circular - Opal diffuser - CCT [3000K/4000K/6000K]+ Wattage Selectable - Black - Emergency - Microwave sensor

Dimensions

C (mm)	85
Dia. (mm)	282

Line Drawing

