

### Order Code: XCBHCBPX1M3MS

X1 Bulkhead WP - Circular - Prismatic diffuser - CCT [3000K/4000K/6000K] + Wattage Selectable - Black - Emergency - Microwave sensor



#### Features

- Suitable for exterior commercial and industrial applications
- Wattage adjustable via selector switch [8W/12W/16W]
- CCT adjustable via selector switch [3000K/4000K/6000K]

#### Construction

- Modular [emergency](#) and [microwave sensor](#)'s available for quick and easy conversion of a standard fitting
- For additional control, please use [X1 Bulkhead Remote](#) [Sold Separately]

#### Installation Notes

3-point screw fixing  
 Conduit side entry points for surface mount cable entry  
 Loop-in, loop-out push-fit terminal block for quick tool-free instalation



#### Technical Data

General		Electrical	
Luminaire Wattage (W)	8W/12W/16W	Rated Input Current (A)	0.04 to 0.08
Weight (kg)	0.82	Power Factor (pf)	0.82 to 0.92
Operating Temperature (ta °C)	5° to 25°	Input Voltage Range (VAC)	198 to 264
		Inrush Current Peak (A)	19.1
Light Output		Surge Protection (kV)	1
Lumens (lm)	1200 to 2120	Conductor Size (mm)	0.5 to 2.5
Efficacy (lm/W)	155	Terminal Type	4 pole piano key
LED			
CCT (K)	3000K/4000K/6000K		
CRI	80		
Macadam Ellipses	0.9 to 1.4		
Driver			
Driver Current (mA)	140/215/280		
Forward Voltage (V)	48.5 to 52.5		
Emergency			
Emergency Lumen Operating	146		
Emergency Wattage (W)	2		

**Order Code: XCBHCBPX1M3MS**

X1 Bulkhead WP - Circular - Prismatic diffuser - CCT [3000K/4000K/6000K] + Wattage Selectable - Black - Emergency - Microwave sensor

Dimensions

C (mm)	85
Dia. (mm)	282

Line Drawing

