

Order Code: XCBHCWPX1M3

X1 Bulkhead WP - Circular - Prismatic diffuser - CCT [3000K/4000K/6000K] + Wattage Selectable - White - Emergency



Features

- Suitable for exterior commercial and industrial applications
- Wattage selectable via selector switch [8W/12W/16W]
- CCT selectable via selector switch [3000K/4000K/6000K]

Construction

- Modular [emergency](#) and [microwave sensor](#)'s available for quick and easy conversion of a standard fitting
- For additional control, please use [X1 Bulkhead Remote](#) [Sold Separately]

Installation Notes

3-point screw fixing
 Conduit side entry points for surface mount cable entry
 Loop-in, loop-out push-fit terminal block for quick tool-free installation



Technical Data

| General | | Electrical | |
|-------------------------------|-------------------|---------------------------|------------------|
| Luminaire Wattage (W) | 8W/12W/16W | Rated Input Current (A) | 0.04 to 0.08 |
| Weight (kg) | 0.81 | Power Factor (pf) | 0.82 to 0.92 |
| Operating Temperature (ta °C) | 5° to 25° | Input Voltage Range (VAC) | 198 to 264 |
| | | Inrush Current Peak (A) | 19.1 |
| Light Output | | Surge Protection (kV) | 1 |
| Lumens (lm) | 1200 to 2120 | Conductor Size (mm) | 0.5 to 2.5 |
| Efficacy (lm/W) | 155 | Terminal Type | 4 pole piano key |
| LED | | | |
| CCT (K) | 3000K/4000K/6000K | | |
| CRI | 80 | | |
| Macadam Elipses | 0.9 to 1.4 | | |
| Driver | | | |
| Driver Current (mA) | 140/215/280 | | |
| Forward Voltage (V) | 48.5 to 52.5 | | |
| Emergency | | | |
| Emergency Lumen Operating | 146 | | |
| Emergency Wattage (W) | 2 | | |

Order Code: XCBHCWPX1M3

X1 Bulkhead WP - Circular - Prismatic diffuser - CCT [3000K/4000K/6000K] + Wattage Selectable - White - Emergency

Dimensions

| | |
|-----------|-----|
| C (mm) | 85 |
| ----- | |
| Dia. (mm) | 282 |
| ----- | |

Line Drawing

