

### Order Code: XCBHX1M3MS

X1 Bulkhead - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency - Microwave sensor



#### Features

- Suitable for most domestic and commercial applications
- CCT selectable via selector switch [3000K/4000K/6000K]
- Wattage selectable via selector switch [8W/12W/16W]
- Twist On/Off diffuser with screwlock suitable for public spaces
- Hinged gear tray for quick and easy installation

#### Construction

- Manufactured from durable thermoplastic materials
- Modular [emergency](#) and [microwave sensor](#)'s available for quick and easy conversion of a standard fitting
- For additional control, please use [X1 Bulkhead Remote](#) [Sold Separately]
- Pre-assembled emergency and sensor luminaires available

#### Installation Notes

Conduit side entry points for surface mount cable entry  
Loop in/out push-fit terminal block for quick installation

### Technical Data

#### General

Luminaire Wattage (W)	8W/12W/16W
Weight (kg)	1.47
Operating Temperature (ta °C)	5° to 25°

#### Light Output

Lumens (lm)	1000 to 1900
Efficacy (lm/W)	130

#### LED

CCT (K)	3000K/4000K/6000K
CRI	80
Macadam Ellipses	1.5 to 9.1

#### Driver

Driver Current (mA)	140 to 215 to 280
Forward Voltage (V)	47.6 to 50

#### Emergency

Emergency Lumen Operating	135
Emergency Wattage (W)	2

#### Electrical

Rated Input Current (A)	0.04 to 0.07
Power Factor (pf)	0.82 to 0.92
Input Voltage Range (VAC)	220 to 240
Inrush Current Peak (A)	18.9
Surge Protection (kV)	1KV
Conductor Size (mm)	0.5 to 2.5
Terminal Type	4 pole piano key

**Order Code: XCBHX1M3MS**

X1 Bulkhead - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency - Microwave sensor

Dimensions

C (mm)	85
Dia. (mm)	320

Line Drawing

