

Order Code: XCBHX1M3MS

X1 Bulkhead - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency - Microwave sensor



Features

- Suitable for most domestic and commercial applications
- CCT adjustable via selector switch [3000K/4000K/6000K]
- Wattage adjustable via selector switch [8W/12W/16W]
- Twist On/Off diffuser with screwlock suitable for public spaces
- Hinged gear tray for quick and easy installation

Construction

- Manufactured from durable thermoplastic materials
- Modular [emergency](#) and [microwave sensor](#)'s available for quick and easy conversion of a standard fitting
- For additional control, please use [X1 Bulkhead Remote](#) [Sold Separately]
- Pre-assembled emergency and sensor luminaires available

Installation Notes

Conduit side entry points for surface mount cable entry
Loop in/out push-fit terminal block for quick installation

Technical Data

General		Electrical	
Luminaire Wattage (W)	8W/12W/16W	Rated Input Current (A)	0.04 to 0.07
Weight (kg)	1.47	Power Factor (pf)	0.82 to 0.92
Operating Temperature (ta °C)	5° to 25°	Input Voltage Range (VAC)	220 to 240
		Inrush Current Peak (A)	18.9
Light Output		Surge Protection (kV)	1KV
Lumens (lm)	1000 to 1900	Conductor Size (mm)	0.5 to 2.5
Efficacy (lm/W)	130	Terminal Type	4 pole piano key
LED			
CCT (K)	3000K/4000K/6000K		
CRI	80		
Macadam Elipses	1.5 to 9.1		
Driver			
Driver Current (mA)	140 to 215 to 280		
Forward Voltage (V)	47.6 to 50		
Emergency			
Emergency Lumen Operating	135		
Emergency Wattage (W)	2		

Order Code: XCBHX1M3MS

X1 Bulkhead - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency - Microwave sensor

Dimensions

C (mm)	85
Dia. (mm)	320

Line Drawing

