

**Order Code: XCEBANM3ST**

XCITE EXIT BOX ST XCEBA 2W - 6500K - Fixed output - non-maintained Emergency Self-test



**Features**

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit top and rear cable entries BESA for wall fix
- Reduced maintenance and high performance
- EURO 1, 2 and 3 running man legend also available [sold separately]

**Construction**

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend
- Integral auto self-test for reduced maintenance, includes a disable function
- Supplied with LiFePO4 battery



**Technical Data**

| General                       |           | Electrical                |                  |
|-------------------------------|-----------|---------------------------|------------------|
| Luminaire Wattage (W)         | 2         | Rated Input Current (A)   | 0.05             |
| Weight (kg)                   | 1.24      | Power Factor (pf)         | 0.17             |
| Operating Temperature (ta °C) | 5° to 25° | Input Voltage Range (VAC) | 220 to 240       |
|                               |           | Conductor Size (mm)       | 1.5              |
|                               |           | Terminal Type             | 3 pole push down |
| Driver                        |           |                           |                  |
| Driver Current (mA)           | 340       |                           |                  |
| Forward Voltage (V)           | 2.49      |                           |                  |

**Order Code: XCEBANM3ST**

XCITE EXIT BOX ST XCEBA 2W - 6500K - Fixed output - non-maintained Emergency Self-test

Dimensions

|        |     |
|--------|-----|
| A (mm) | 392 |
| B (mm) | 190 |
| C (mm) | 60  |

Line Drawing

