

Order Code: XCNC4X1M3

1200mm - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency



Features

- Suitable for a range of commercial and industrial applications
- Available in 4 lengths [2ft, 4ft, 5ft, and 6ft]
- CCT adjustable via selector switch [3000K/4000K/6000K]
- Wattage adjustable via 2-way dip switch [21W/26W/31W/36]
- Position adjustable mounting clips
- Stainless steel retainer clips for diffuser with anti-tamper screw

Construction

- Grey polycarbonate body
- Weatherproof IP65 construction
- Modular [emergency pack](#) and [microwave sensor](#)'s available for quick and easy conversion of a standard fitting
- Pre-assembled emergency and sensor luminaires available

Installation Notes

Conduit and BESA fixing points for end or rear cable entry
Loop in/out push-fit terminal block for quick installation

Technical Data

General

| | |
|-------------------------------|----------------|
| Luminaire Wattage (W) | 21W/26W/31W/36 |
| Weight (kg) | 2.17 |
| Operating Temperature (ta °C) | +5° to +25° |

Light Output

| | |
|-----------------|-------------|
| Lumens (lm) | 3500 - 5900 |
| Efficacy (lm/W) | 164 |

LED

| | |
|------------------|-------------------|
| CCT (K) | 3000K/4000K/6000K |
| CRI | 80 |
| Macadam Ellipses | 7.6 |

Driver

| | |
|---------------------|--------------------|
| Driver Current (mA) | 200, 250, 300, 350 |
| Forward Voltage (V) | 91.7 to 99.1Vdc |

Emergency

| | |
|---------------------------|-----|
| Emergency Lumen Operating | 327 |
| Emergency Wattage (W) | 2 |

Electrical

| | |
|---------------------------|------------------|
| Rated Input Current (A) | 0.1 to 0.17 |
| Power Factor (pf) | 0.93 to 0.97 |
| Input Voltage Range (VAC) | 220 to 240 |
| Inrush Current Peak (A) | 32A |
| Surge Protection (kV) | 1 |
| Conductor Size (mm) | 0.5 to 2.5 |
| Terminal Type | 4 pole piano key |

Order Code: XCNC4X1M3

1200mm - CCT [3000K/4000K/6000K] + Wattage Selectable - Emergency

Dimensions

| | |
|--------|------|
| A (mm) | 1275 |
| B (mm) | 95 |
| B (mm) | 80 |
| Fix | 600 |

Line Drawing

