

**Order Code: XCSEBAM3ST**

XCITE EXIT BOX S ST 2W - 6500K - Fixed output - Emergency Self-test



**Features**

- Suitable for escape routes and exits
- Rear BESA fix and 3 additional rear fixing points
- Dual LED array for internal illumination and downward distribution
- Reduced maintenance and high performance
- Only 30mm depth for modern, slimline appearance
- Supplied with LiFePO4 battery

**Construction**

- Plastic body
- Hinged front lid for easy installation
- Supplied with universal EURO running man legend
- Integral auto self-test for reduced maintenance, includes a disable function



**Technical Data**

| General                       |           | Electrical                |                   |
|-------------------------------|-----------|---------------------------|-------------------|
| Luminaire Wattage (W)         | 2         | Rated Input Current (A)   | 0.04              |
| Weight (kg)                   | 0.61      | Power Factor (pf)         | 0.18              |
| Operating Temperature (ta °C) | 5° to 25° | Input Voltage Range (VAC) | 220 to 240        |
|                               |           | Conductor Size (mm)       | 1.5               |
|                               |           | Terminal Type             | 4 pole screw down |
| Driver                        |           |                           |                   |
| Driver Current (mA)           | 172       |                           |                   |
| Forward Voltage (V)           | 3.37      |                           |                   |

**Order Code:** XCSEBAM3ST

XCITE EXIT BOX S ST 2W - 6500K - Fixed output - Emergency Self-test

Dimensions

|        |     |
|--------|-----|
| A (mm) | 325 |
| B (mm) | 185 |
| C (mm) | 30  |

Line Drawing

